

Agilent 33250A Function/Arbitrary Waveform Generator

Data Sheet



- 80 MHz sine and square wave outputs
- Sine, square, ramp, noise and other waveforms
- 50 MHz pulse waveforms with variable rise/fall times
- 12-bit, 200 MSa/s, 64K-point deep arbitrary waveform

with a programmable frequency marker signal. Programmable burst count and gating allow you to further customize your signal.

For system applications, both GPIB and RS-232 interfaces are standard, and support full programmability using SCPI commands.

Standard Waveforms

The Agilent Technologies 33250A Function/Arbitrary Waveform Generator uses direct digital-synthesis techniques to create a stable, accurate output on all waveforms, down to 1 μ Hz frequency resolution. The benefits are apparent in every signal you produce, from the sine wave frequency accuracy to the fast rise/fall times of square waves, to the ramp linearity.

Front-panel operation of the 33250A is straightforward and user friendly. The knob or numeric keypad can be used to adjust frequency, amplitude and offset. You can even enter voltage values directly in Vpp, Vrms, dBm, or high/low levels. Timing parameters can be entered in hertz (Hz) or seconds.

Custom Waveform Generation

Why settle for a basic function generator when you can get arbitrary waveforms at no extra cost? With the 33250A, you can generate arbitrary waveforms with 12-bit vertical resolution, 64K memory depth, and a sample rate of 200 MSa/s. You can also store up to four 64K-deep arbitrary waveforms in non-volatile memory with

user-defined names to help you find the right waveform when you need it most.

The included Agilent IntuiLink software allows you to easily create, edit, and download complex waveforms using the IntuiLink Arbitrary Waveform Editor. Or you can capture a waveform using IntuiLink oscilloscope or DMM and send it to the 33250A for output. For programmers, ActiveX components can be used to control the instrument using SCPI commands. IntuiLink provides the tools to easily create, download, and manage waveforms for your 33250A. To find out more about IntuiLink, visit www.agilent.com/find/intuilink.

Pulse Generation

The 33250A can generate simple pulses up to 50 MHz. With variable edge time, pulse width and voltage level, the 33250A is ideally suited to a wide variety of pulse applications.

Built-in Versatility

AM, FM and FSK capabilities make it easy to modulate waveforms with or without a separate source. Linear or logarithmic sweeps can be performed

Color Graphical Display

The unique design of the 33250A combines a low-profile instrument with the benefits of a color graphical display. Now you can display multiple waveform parameters at the same time. The graphical interface also allows you to modify arbitrary waveforms quickly and easily.

Timebase Stability and Clock Reference

The 33250A TCXO timebase gives you frequency accuracy of 1 ppm for your most demanding applications. The external clock reference input/output lets you synchronize to an external 10 MHz clock, to another 33250A, or to an Agilent 33120A. Phase adjustments can be made from the front panel or via a computer interface, allowing precise phase calibration and adjustment.

3-year Warranty

The 33250A ships standard with operating and service manuals, a quick reference guide, test data, and a full three-year warranty - one of the best coverage plans in the industry.



Agilent Technologies

WAVEFORMS

Standard	sine, square, pulse, ramp, noise, sin(x)/x, exponential rise, exponential fall, cardiac, DC volts
-----------------	---

Arbitrary

Waveform length	1 to 64K points
Amplitude resolution	12 bits (including sign)
Repetition rate	1 μ Hz to 25 MHz
Sample rate	200 MSa/s
Filter bandwidth	50 MHz
Non-vol. memory	Four (4) 64K waveforms

FREQUENCY CHARACTERISTICS

Sine	1 μ Hz to 80 MHz
Square	1 μ Hz to 80 MHz
Pulse	500 μ Hz to 50 MHz
Arb	1 μ Hz to 25 MHz
Ramp	1 μ Hz to 1 MHz
White noise	50 MHz bandwidth
Resolution	1 μ Hz; except pulse, 5 digits
Accuracy	
Stability	± 0.3 ppm, 18°C to 28°C ± 1 ppm, 0°C to 50°C
Aging	± 1 ppm per 1 year

SINEWAVE SPECTRAL PURITY

Harmonic distortion

	≤ 3 Vpp ¹	> 3 Vpp
DC to 1 MHz	-60 dBc	-55 dBc
1 to 5 MHz	-57 dBc	-45 dBc
5 to 80 MHz	-37 dBc	-30 dBc

Total harmonic distortion

DC to 20 kHz	$< 0.2\% + 0.1$ mVrms
--------------	-----------------------

Spurious (non-harmonic)²

DC to 1 MHz	-60 dBc
1 to 20 MHz	-50 dBc
20 80 MHz	-50 dBc + 6 dBc/octave

Phase noise (30 kHz band)

10 MHz	< -65 dBc (typical)
80 MHz	< -47 dBc (typical)

SIGNAL CHARACTERISTICS

Squarewave

Rise/Fall time	< 8 ns
Overshoot	$< 5\%$
Asymmetry	1% of period + 1 ns
Jitter (rms)	
< 2 MHz	0.01% + 525 ps
≥ 2 MHz	0.1% + 75 ps
Duty cycle	
≤ 25 MHz	20.0% to 80.0%
25 to 50 MHz	40.0% to 60.0%
50 to 80 MHz	50.0% fixed

Pulse

Period	20.00 ns to 2000.0 s
Pulse width	8.0 ns to 1999.9 s
Variable edge time	5.00 ns to 1.00 ms
Overshoot	$< 5\%$
Jitter (rms)	100 ppm + 50 ps

Ramp

Linearity	$< 0.1\%$ of peak output
Symmetry	0.0% - 100.0%

Arb

Min. edge time	< 10 ns
Linearity	$< 0.1\%$ of peak output
Settling time	< 50 ns to 0.5% of final value
Jitter (rms)	30 ppm + 2.5 ns

OUTPUT CHARACTERISTICS

Amplitude (into 50 Ω)	10 mVpp to 10 Vpp
Accuracy (at 1 kHz, > 10 mVpp, Autorange)	$\pm 1\%$ of setting ± 1 mVpp
Flatness (sinewave relative to 1 kHz, Autorange)	
< 10 MHz	$\pm 1\%$ (0.1 dB)
10 to 50 MHz	$\pm 2\%$ (0.2 dB)
50 to 80 MHz	$\pm 5\%$ (0.4 dB)
Units	Vpp, Vrms, dBm, high and low level
Resolution	0.1 mV or 4 digits
Offset (into 50 Ω)	± 5 Vpk ac + dc
Accuracy	1% of setting + 2 mV + 0.5% of amplitude

Waveform Output

Impedance	50 Ω typical (fixed) > 10 M Ω (output disabled)
Isolation	42 Vpk maximum to earth
Protection	short-circuit protected; overload automatically disables main output

MODULATION

AM

Carrier waveforms	sine, square, ramp, and arb
Mod. waveforms	sine, square, ramp, noise, and arb
Mod. frequency	2 MHz to 20 kHz
Depth	0.0% to 120.0%
Source	internal/external

FM

Carrier waveforms	sine, square, ramp, and arb
Mod. waveforms	sine, square, ramp, noise, and arb
Mod. frequency	2 MHz to 20 kHz
Deviation range	DC to 80 MHz
Source	internal/external

FSK

Carrier waveforms	sine, square, ramp, and arb
Mod. waveform	50% duty cycle square
Internal rate	2 MHz to 1 MHz
Frequency range	1 μ Hz to 80 MHz
Source	internal/external

External Modulation Input

Voltage range	± 5 V full scale
Input impedance	10 k Ω
Frequency	DC to 20 kHz

BURST

Waveforms	sine, square, ramp, pulse, arb, and noise
Frequency	1 μ Hz to 80 MHz ²
Burst count	1 to 1,000,000 cycles or infinite
Start/Stop phase	-360.0° to +360.0°
Internal period	1 ms to 500 s
Gate source	external trigger
Trigger source	single manual trigger, internal, external trig
Trigger delay	
N-cycle, infinite	0.0 ns to 85.000 sec

SWEEP

Waveforms	sine, square, ramp, and arb
Type	linear and logarithmic
Direction	up or down
Start F/Stop F	100 μ Hz to 80 MHz
Sweep time	1 ms to 500 s
Trigger	single manual trigger, internal, external trig
Marker	falling edge of sync signal (programmable)

SYSTEM CHARACTERISTICS

Configuration Times (typical)

Function change	
Standard	100 ms
Pulse	660 ms
Built-in arb	220 ms
Frequency change	20 ms
Amplitude change	50 ms
Offset change	50 ms
Select user arb	< 900 ms for < 16K pts.
Modulation change	< 200 ms

Arb Download Times GPIB/RS-232 (115Kbps)

Arb Length	Binary	ASCII Integer	ASCII Real
64K points	48 sec	112 sec	186 sec
16K points	12 sec	28 sec	44 sec
8K points	6 sec	14 sec	22 sec
4K points	3 sec	7 sec	11 sec
2K points	1.5 sec	3.5 sec	5.5 sec

TRIGGER CHARACTERISTICS

Trigger input

Input level	TTL compatible
Slope	rising or falling, selectable
Pulse width	> 100 ns
Input impedance	10 k Ω , DC coupled
Latency	
Burst	< 100 ns (typical)
Sweep	< 10 μ s (typical)
Jitter (rms)	
Burst	1 ns; except pulse, 300 ps
Sweep	2.5 μ s

Trigger output

Level	TTL compatible into 50 Ω
Pulse width	> 450 ns
Maximum rate	1 MHz
Fanout	\leq 4 Agilent 33250A's

CLOCK REFERENCE

Phase Offset

Range	-360° to +360°
Resolution	0.001°

External Reference Input

Lock range	10 MHz \pm 35 kHz
Level	100 mVpp to 5 Vpp
Impedance	1 k Ω nominal, ac coupled
Lock time	< 2 s

Internal Reference Output

Frequency	10 MHz
Level	632 mVpp (0 dbm), nominal
Impedance	50 Ω nominal, ac coupled

SYNC OUTPUT

Level	TTL compatible into > 1 k Ω
Impedance	50 Ω nominal

GENERAL

Power supply	100-240 V, 50-60 Hz 100-127 V, 50-400 Hz
Power consumption	140 VA
Operating temp.	0°C to 55°C
Storage temp.	-30°C to 70°C
Stored states	4 named user configurations
Power on state	default or last
Interface	IEEE-488 and RS-232 std.
Language	SCPI-1997, IEEE-488.2
Dimensions (WxHxD)	
Bench top	254 x 104 x 374 mm
Rackmount	213 x 89 x 348 mm
Weight	4.6 kg
Safety designed to	EN61010-1, CSA1010.1, UL-311-1
EMC tested to	EN55011, IEC-1326-1
Vibration and shock	MIL-T-28800E, Type III, Class 5
Acoustic noise	40 dBA
Warm-up time	1 hour
Calibration interval	1 year
Warranty	3 years standard

¹ Harmonic distortion at low amplitudes is limited by a -70 dBm floor

² Spurious noise at low amplitudes is limited by a -75 dBm floor

³ Sine and square waveforms above 25 MHz only with infinite burst count

Ordering Information

Agilent 33250A

Function/Arbitrary
Waveform Generator

Accessories Included

Operating manual, service manual, quick reference guide, IntuiLink connectivity software, test data, RS-232 cable, and power cord.

Options

Opt. 1CM Rackmount kit*
(Agilent 34190A)

Opt. W50 Additional 2-year
warranty (5-year total)

Accessories

10100C 50Ω feedthru
11094B 75Ω feedthru
11095A 600Ω feedthru
34131A Carrying case
34161A Accessory pouch
34190A Rackmount kit*
34811A BenchLink Arb software

*For racking two 33250As side-by-side, order the following items:

Lock-link kit (p/n 5061-9694)
Flange kit (p/n 5063-9212)

Agilent Technologies' Test and Measurement Support, Services, and Assistance

Agilent Technologies aims to maximize the value you receive, while minimizing your risk and problems. We strive to ensure that you get the test and measurement capabilities you paid for and obtain the support you need. Our extensive support resources and services can help you choose the right Agilent products for your applications and apply them successfully. Every instrument and system we sell has a global warranty. Support is available for at least five years beyond the production life of the product. Two concepts underlie Agilent's overall support policy: "Our Promise" and "Your Advantage."

Our Promise

Our Promise means your Agilent test and measurement equipment will meet its advertised performance and functionality. When you are choosing new equipment, we will help you with product information, including realistic performance specifications and practical recommendations from experienced test engineers. When you use Agilent equipment, we can verify that it works properly, help with product operation, and provide basic measurement assistance for the use of specified capabilities, at no extra cost upon request. Many self-help tools are available.

Your Advantage

Your Advantage means that Agilent offers a wide range of additional expert test and measurement services, which you can purchase according to your unique technical and business needs. Solve problems efficiently and gain a competitive edge by contracting with us for calibration, extra-cost upgrades, out-of-warranty repairs, and on-site education and training, as well as design, system integration, project management, and other professional engineering services. Experienced Agilent engineers and technicians worldwide can help you maximize your productivity, optimize the return on investment of your Agilent instruments and systems, and obtain dependable measurement accuracy for the life of those products.

By internet, phone, or fax, get assistance with all your test & measurement needs

Online assistance:
www.agilent.com/find/assist

Phone or Fax
United States:
(tel) 1 800 452 4844

Canada:
(tel) 1 877 894 4414
(fax) (905) 282 6495

Europe:
(tel) (31 20) 547 2323
(fax) (31 20) 547 2390

Japan:
(tel) (81) 426 56 7832
(fax) (81) 426 56 7840

Latin America:
(tel) (305) 269 7500
(fax) (305) 269 7599

Australia:
(tel) 1 800 629 485
(fax) (61 3) 9210 5947

New Zealand:
(tel) 0 800 738 378
(fax) 64 4 495 8950

Asia Pacific:
(tel) (852) 3197 7777
(fax) (852) 2506 9284

Product specifications and descriptions in this document subject to change without notice.

Copyright © 2001 Agilent Technologies
Printed in USA May 2, 2001
5968-8807EN



Agilent Technologies